

Casolux Marine light

Marine light system

PIA POWERBANK

GB

IP68
[7m]



Power
1 - 3,5 w

Efficiency
100 Lm/w

Lifetime
36.000 Hours
(70% Lumen maintenance)

Input
5 VDC


Material
PC



PIA large



PIA small in magnetic holders



Micro USB input

USB output



Hook



Magnetic holders



	L	D	Weight
Pia small	143mm	36mm	130 gram
Pia large	262mm	36mm	210 gram

Pia small specifications

Gears	Brightness	Batterytime
White light 1	10%	60 hours
White light 2	100%	8 hours
Red light	100%	15 hours
Red quick flashing	100%	15 hours
SOS flashing	100%	31 hours
Charging time	5V, >1A adapter	5 hours

Pia large specifications

Gears	Brightness	Batterytime
White light 1	10%	72 hours
White light 2	100%	10 hours
White light 3	100%	5 hours
White flashing light	100%	20 hours
Charging time	5V, >1A adapter	5 hours

Product code	Lumen output	Power	CCT	Battery	Input	Output
PIA-SMALL-POWER-SUPPLY-1W	100 lm	1 w	5700K	3,7V, 2600mAh	5V, 800mA	5V, 1200mA
PIA-LARGE-POWER-SUPPLY-3,5W	350 lm	3,5 w	5700K	3,7V, 5200mAh	5V, 2000mA	5V, 2000mA

PIA-MAGNET

Feature

- IP68 LED multi-light and Power Bank for charging electronic products: Smartphone, tablet and so on
- Flashing emergency light. PIA SMALL has SOS Morse code signal light
- Charged from adapter 5V 1A, from powerbank or from computer to micro USB output
- Connect to the rechargeable electronic product in USB Type A output
- Metal hook in end to hang the lamp in
- Available with magnetic holders

Material

- Lithium-Ion battery
- PC tube (Polycarbonat)

Benefit

- High reliability
- Maintenance free

Application

- Marine light. Emergency light

